

# 數字式頻率錶 DIGITAL FREQUENCY METER



FP - 40 4 digits Frequency Meter


## ■ Features

- Accuracy  $\pm 0.03\%$
- DIN case 96×48mm

## ■ Specifications

- Display** : 4 digits (9999), 0.56" LED high
- Conversion Rate** : 1/sec.
- Accuracy** :  $\pm 0.03\%$  ( $23 \pm 5^\circ\text{C}$ )
- Operating Temp.** :  $0 \sim 60^\circ\text{C}$  / below 80% R.H.
- Storage Temp.** :  $-10 \sim 70^\circ\text{C}$  / below 70% R.H.
- Power Supply** : AC 115/230V  $\pm 10\%$ , 50/60Hz
- Power Consumption** : Approx. 2VA
- Dielectric Strength** : AC 1500V/1min (Input/Power)
- Insulation Resistance** : More than 100M $\Omega$  at 500VDC
- Dimensions** : 96(W) x 48(H) x 104(D)mm
- Panel Cut-Out** : 91.4(W) x 44(H)mm

## ■ Connection Diagram



## ■ Order Code

